

# 6000VA, 3-Phase to 3-Phase Frequency Converter with Sine-wave Output

## Rugged, Industrial Quality

### FTT 6K

- 3-Phase sinewave output voltage
- Filtered input/output
- Cooling by internal fans
- Full electronic protection
- Field-proven design topology

6U x 19"  
(4 x 3U3) for 380V  
output version.



9U x 19"  
for 208V  
output  
version.



Mechanical size depends on input/output configuration.  
Chassis mount versions are also available.

This rugged, modular AC-AC frequency converter uses microprocessor controlled high frequency PWM technology to deliver 3-Phase, 6000VA continuous sine-wave output power from a 3-phase input. It is a mature design with a track record in numerous applications. The standard 3-phase outputs are 208V, 380V or 400V (L-L). The output neutrals are internally connected to the chassis in "Y" configuration; the phase-to-neutral voltages (115V, 220V or 230V) are therefore also available. The module combination of the system depends on the input/output. Each interconnection between modules is made with a single pair of wires. High quality built-in fans provide sufficient airflow for operation within the specified temperature range without de-rating. The fans draw air into the unit, and exhaust at the terminal side of the unit. All heat generating components are installed on aluminum heatsink blocks which are thermally connected to the base plate. Conformal coating provides protection against humidity and airborne contaminants. Full electronic protection eliminates the possibility of failure due to abnormal operating conditions, including application errors. Low component count and the use of components with established reliability results in high MTBF. The unit is manufactured at our plant under strict quality control. Customized versions are also available.

### SPECIFICATIONS

#### Input Voltage

208Vac (L-L) +/-15% 3-phase  
380V or 400Vac (L-L) +/-15%  
3-phase  
47 ... 410Hz are standard  
Factory set for required input

#### Input Protection

Inrush current limiting  
Varistors  
Internal safety fuse  
Lower voltage than the specified  
minimum input will not damage  
the unit

#### Isolation

According to the  
corresponding input/output  
combination, as minimum:

2250Vdc input to chassis,  
4300Vdc input to output,  
8mm spacing  
1500Vdc output to chassis

#### Standards

Designed to meet  
C22.2 No. 107.1 - 01,  
UL 458 and EN60950-1

#### EMI

EN 55032 Class A with margins  
Class B filtering available

#### Output Voltage

208Vac (L-L)/3-phase continuous  
60 or 400Hz or  
380Vac or 400Vac (L-L)/3-phase  
continuous 50 or 60Hz  
All neutrals are internally  
connected to chassis (GND) in "Y"  
configuration  
(Phase-to-neutral voltages can also  
be used: 115Vac, 220Vac or 230Vac)  
Consult factory for other voltages,  
frequencies and options

#### Output Wave Form

Sinusoidal

#### Total Harmonic Distortion

Less than 5% at full load

#### Line/Load Regulation

Maximum  $\pm 6\%$  from no load  
to full load.

#### Load Crest Factor

Maximum 2.5 at 90% load

#### Output Noise

High frequency ripple is less  
than 500mVrms (20MHz BW)

#### Output Overload Protection

Current limiting with short circuit  
protection.  
Thermal shutdown with automatic  
recovery in case of insufficient  
cooling

#### Output Overvoltage Protection

Output voltage is limited by  
internal supply voltage

#### Efficiency

Depends on input and output  
voltage combination.  
Typically 80% at full load

#### Operating Temperature Range

0° C to +50° C for full specification  
without derating.  
Extended temperature ranges  
available

#### Temperature Drift

0.05% per °C over operating  
temperature range

#### Cooling

Built-in fans drawing air into  
the unit

#### Environmental Protection

Basic ruggedizing  
Full ruggedizing and conformal  
coating available as option

#### Shock/Vibration

IEC 61373 Cat 1 A&B

#### Humidity

5 - 95% non-condensing

#### MTBF

Min. 75,000 hours at 45°C  
Demonstrated MTBF is  
significantly higher  
Fans excluded

#### Indicators

None

#### Control Input

None  
Remote shutdown or enable as  
option

#### Alarm Output

None  
Option: output fail alarm (Form C)

#### Package/Dimensions (H x W)

Package varies from 6U x 19" to  
9U x 19", depending on input/output  
combination required.  
The 6U x 19" version is typically  
built with four 3U3 size modules  
The 9U x 19" version with one 3U7  
size chassis and three 3U3 size modules  
Chassis-mount versions are available  
at the same price

#### Weight

6U x 19" version: 28 kg (62 lb.)  
9U x 19" version: 33 kg (73 lb.)

#### Connections

Input: Terminal block  
Output: Terminal block  
Interconnections: Terminal blocks

#### RoHS Compliance

Fully compliant

#### Warranty

Two years subject to application  
within good engineering practice

**Enhancements to these general specifications can be accommodated upon request. Specifications are subject to change**

*Designer and manufacturer of quality ac-dc power supplies and battery chargers, converters, inverters, dc-output UPS systems, complete rack mount systems and DC-input fluorescent lamp inverters since 1982. Custom or standard. ABSOPULSE is a BABT-approved Facility.*

**ABSOPULSE**  
ELECTRONICS LTD.

#### ABSOPULSE ELECTRONICS LTD

110 Walgreen Road, Ottawa, Ontario. K0A 1L0. CANADA  
Tel: +1-613-836-3511 | Fax: +1-613-836-7488  
<http://www.absopulse.com>